

# HH

## säkringar

Högeffektsäkringar  
Delområdes



### Högeffektsäkring 6/12kV - 292 mm

Märkström	Ifö-nr	E-nr	Trafo (kVA)	I <sub>0,1</sub> s(A)	I <sub>min</sub> (A)	I <sub>1</sub> (kA)
6A	186501201	20 591 22	50*	43	25	63
10A	186501302	20 591 46	100*	70	46	63
16A	186501303	20 591 48	-	85	60	63
20A	186501304	20 591 50	200*	115	80	63
25A	186501315	20 591 51	-	126	105	63
32A	186501305	20 591 52	315&(400)*	170	130	63
40A	186501306	20 591 54	500&630*	250	178	63
50A	186501307	20 591 56	800*	360	220	63
63A	186501308	20 591 58	1000*	440	270	63
80A	186501309	20 591 60	(1250)*	570	360	63
100A	186501320	20 591 35	N/A	1121	360	63
125A	186501322	20 591 37	N/A	1493	450	63
160A	186501324	20 591 39	N/A	1803	600	63

### Högeffektsäkring 10/24kV - 442 mm

Märkström	Ifö-nr	E-nr	Trafo (kVA)	I <sub>0,1</sub> s(A)	I <sub>min</sub> (A)	I <sub>1</sub> (kA)
4A	186502200	20 591 30	50*	19	20	6
6A	186502401	20 591 72	100*	43	25	63
10A	186502302	20 591 84	200&315*	70	46	63
16A	186502303	20 591 86	-	85	60	63
20A	186502304	20 591 88	(400)&500*	115	80	63
25A	186502305	20 591 90	630*	126	105	63
32A	186502306	20 591 92	800*	170	130	63
40A	186502307	20 591 94	1000&1250*	250	178	63
50A	186502313	20 591 73	N/A	424	175	63
63A	186502314	20 591 74	N/A	555	220	63
80A	186502315	20 591 75	N/A	743	280	63
100A	186502316	20 591 76	N/A	1121	355	63
125A	186502317	20 591 77	N/A	1345	473	63

### Högeffektsäkring 6/12kV - 442 mm

Märkström	Ifö-nr	E-nr	Trafo (kVA)	I <sub>0,1</sub> s(A)	I <sub>min</sub> (A)	I <sub>1</sub> (kA)
100A	186501321	20 591 36	N/A	1121	360	63
125A	186501323	20 591 38	N/A	1493	450	63
160A	186501325	20 591 40	N/A	1803	600	63

\*Uppfyller kraven för Sverigesäkring.

**IFÖ ELECTRIC**  
säkert i ledningen

www.ifolectric.com  
Tel 0456 - 265 00